


**GRFA Short**


**Description:** Chassis mount solderable female RCA. Mounts to chassis thickness of 0.125"/3.18mm or less. Comes with red and white 0.625"/15.87mm outside diameter shoulder washers for channel identification. Standard mounting nut is gold plated brass 0.138"/3.51mm thick. Ideal mounting hole diameter 0.455"/11.55mm.

**Base metal:** High copper content, non-magnetic brass.

**Plating:** Silver/rhodium

**Termination:** Solder cup for positive, chassis/notch for negative.


**GRFA Long**


**Description:** Chassis mount solderable female RCA. Mounts to chassis thickness of 0.342"/8.70mm or less. Comes with red and white 0.625"/15.87mm outside diameter shoulder washers for channel identification. Standard mounting nut is gold plated brass 0.138"/3.51mm thick. Ideal mounting hole diameter 0.455"/11.55mm.

**Base metal:** High copper content, non-magnetic brass.

**Plating:** Silver/rhodium

**Termination:** Solder cup for positive, chassis/notch for negative.


**GRFA DBL PRT G**


**Description:** PCB double female RCA. Mounts to chassis thickness of 0.228"/5.80mm or less. Comes with red and white 0.625"/15.87mm outside diameter shoulder washers for channel identification. Standard mounting nut is gold plated brass 0.138"/3.51mm thick. Ideal mounting hole diameter 0.455"/11.55mm.

**Base metal:** High copper content, non-magnetic brass.

**Plating:** Gold

**Termination:** PCB


**GRFA PRT**


**Description:** PCB female RCA. Mounts to chassis thickness of 0.170"/4.32mm or less. Comes with red and white 0.625"/15.87mm outside diameter shoulder washers for channel identification. Standard mounting nut is gold plated brass 0.138"/3.51mm thick. Ideal mounting hole diameter 0.455"/11.55mm.

**Base metal:** High copper content, non-magnetic brass.

**Plating:** Silver/rhodium

**Termination:** PCB

**GRFA PSR2 M**


**Description:** PCB female RCA. Mounts to chassis thickness of 0.5"/12.72mm or less. Comes with red and white 0.625"/15.87mm outside diameter shoulder washers for channel identification. Detachable metal washer for backing plate. Standard mounting nut is gold plated brass 0.188"/4.8mm thick. Ideal mounting hole diameter 0.455"/11.55mm.

**Base metal:** High copper content, non-magnetic brass.

**Plating:** Silver/rhodium

**Termination:** PCB

**GRFA PSA**


**Description:** PCB female RCA. Mounts to chassis thickness of 0.5"/12.72mm or less. Comes with red and white 0.625"/15.87mm outside diameter shoulder washers for channel identification. Detachable metal washer for backing plate. Standard mounting nut is gold plated brass 0.188"/4.8mm thick. Ideal mounting hole diameter 0.455"/11.55mm.

**Base metal:** High copper content, non-magnetic brass.

**Plating:** Silver/rhodium

**Termination:** PCB

**CTFA**


**Description:** Chassis mount solderable female RCA. Mounts to chassis thickness of 0.225"/5.73mm or less. Comes with red or white 0.590"/15.0mm outside diameter shoulder washers. Ideal mounting hole diameter 0.37"/9.50mm. Comes with a gold plated solderable ground tab.

**Base metal:** Brass.

**Plating:** Silver/rhodium

**Termination:** Solder cup for positive, removable ground tab for ground